

//

MAZ-6600RU

AMPLIFICADOR DE MEGAFONÍA MATRICIAL Y MULTICANAL

ESPECIALMENTE RECOMENDADO EN:

Todos los sectores



DESCRIPCIÓN

Amplificador de megafonía matricial y multicanal con matriz de 5 canales de entrada a 6 zonas de salida con control independiente de volumen. Incorpora un reproductor USB/SD/MP3 con sintonizador digital de radio FM. Los canales de entrada tienen controles de graves, agudos, volumen y asignación a zonas. Las zonas de salida tienen control independiente de volumen. Indicado para instalaciones comerciales con varias zonas y diferentes programas musicales.



Amplia la información del producto en:

<https://fonestar.com/ES/MAZ-6600RU>

CARACTERÍSTICAS TÉCNICAS

CHARACTERISTICS	<p>Matrix and multi-channel amplifier. Allocation matrix of 5 input channels to 6 output zones. USB/SD player for MP3 files. Digital FM radio tuner. 6 zones with independent volume control. Phantom power supply. Musical chimes. Paging priority. Remote control for USB/SD/MP3/FM player.</p>
POWER	6 x 100 W RMS
RESPONSE	80-18,000 Hz \pm 3 dB
DISTORTION	Harmonic: < 0.5%
S/N RATIO	Microphones: > 65 dB Aux: > 75 dB
INPUTS	<p>1 unbalanced mic., 6.3 mm jack, 4 mV RMS 2 balanced mics/lines, combo (XLR and 6.3 mm jack) 4 mV RMS / 400 mV RMS, switchable 1 DVD/CD/AUX stereo aux, 2 x RCA 220 mV RMS, 160 mV RMS, 110 mV RMS, selectable 1 stereo aux, 3.5 mm jack, 200 mV RMS</p>
OUTPUTS	1 stereo monitor, 6.3 mm jack
CONTROLS	<p>6 zone buttons (1 to 6) for each input channel (2 to 5) and USB/SD/MP3/FM player Channels 1 to 4: volume control, bass and treble Zones 1 to 6: volume control, monitor selector Monitor volume</p>
PLAYER	USB/SD/MP3 player and digital FM tuner with preset channels and auto scan
PHANTOM	48 V in mics 2 to 3, selectable
PRIORITY	Mic. 1 through signal level or contact closure, selectable
IMPEDANCE	6 zones: 8 Ω and 100 and 70 V lines, screw terminals
POWER SUPPLY	230/115 V AC, 1,000 W maximum



Amplia la información del producto en:

<https://fonestar.com/ES/MAZ-6600RU>

DIMENSIONS	420 x 133 x 376 mm depth. 3 U 19" rack
WEIGHT	17.15 kg
ACCESSORIES	FM antenna Mounts for assembling in 19" rack



Amplia la información del producto en:

<https://fonestar.com/ES/MAZ-6600RU>