

//

MPX-4088

MATRIZ DE AUDIO 8 X 8 CON DANTE

ESPECIALMENTE RECOMENDADO EN:

Todos los sectores



DESCRIPCIÓN

Mando remoto de entrada/salida de audio para matriz mod. MPX-4088.
2 canales de entrada y 2 canales de salida. Conexión mediante cable Cat 5e.



Amplia la información del producto en:

<https://fonestar.com/ES/MPX-4088>

CARACTERÍSTICAS TÉCNICAS

CHARACTERISTICS	<p>Audio matrix with 8 analogue input channels to 8 output zones. 4 configurable input/output digital channels for use with controls mod. MPX-400MIC, MPX-410ES, MPX-430VS. Optional zone controls, mod. MPX-420V and MPX-430VS for program selection in the zone where the program is broadcast. PC control software. LED indicators for power, bus occupation, signal and failure. LCD information display. Microphone with priority and optional zone selection mod. MPX-400MIC. DANTE compatible.</p>
INPUTS	<p>8 balanced line, euroblock 6,800 Ω, 7.74 Vrms maximum 2 RD ports, for mod. MPX-420V, MPX-430VS, MPX-410ES, MPX-400MIC or MPX-440X, RJ-45 1 RC-Net port for matrix interconnection, RJ-45 1 LAN port for connection to local area network, RJ-45</p>
OUTPUTS	<p>8 balanced lines, euroblock 240 Ω, 7.74 Vrms maximum 2 RD ports, for mod. MPX-420V, MPX-430VS, MPX-410ES, MPX-400MIC or MPX-440X, RJ-45 1 extension link, RC-Net, RJ-45 RS-232 port, euroblock</p>
CONTROLS	<p>PC control software (input and output routing, DSP functions, equalization, noise gates, compressor, gain control, etc.) TCP/IP and RS-232 protocol for integration with other systems</p>
RESPONSE	20-20,000 Hz \pm 1.5 dB
DISTORTION	Harmonic: < 0.01%
S/N RATIO	<p>Microphone > 102 dB Lines > 107 dB</p>
PHANTOM	48 V in inputs 1 to 8, selectable with software
PRIORITY	<p>Microphone with optional zone selector mod. MPX-400MIC Inputs 1 to 8 through level, selectable with software</p>
POWER SUPPLY	100-240 V AC, 80 W
DIMENSIONS	483 x 44 x 256 mm depth. 1 U 19" rack
WEIGHT	4.3 kg



Amplia la información del producto en:

<https://fonestar.com/ES/MPX-4088>

OPTIONAL

MPX-400MIC: Microphone with zone selector
MPX-410ES: Audio input/output control
MPX-420V: Zone control
MPX-430VS: Zone control with stereo output
MPX-460P: Touch screen control
MPX-440X: RD port extender
MPX-450D: DANTE Module



Amplia la información del producto en:

<https://fonestar.com/ES/MPX-4088>