

//

PROX-15

AMPLIFICADOR DE MEGAFONÍA MONOZONA

ESPECIALMENTE RECOMENDADO EN:

Todos los sectores



DESCRIPCIÓN

Gracias a nuestra dilatada experiencia en sistemas de amplificación, FONESTAR ha diseñado una nueva gama de amplificadores de megafonía de grandes prestaciones, diseño y construcción, la gama PROX. Se trata de una solución perfecta que integra mezclador, etapa de potencia, reproductor USB/MP3/FM, entradas de micrófono y auxiliar en un mismo equipo, para instalaciones de megafonía con altavoces de 100 V o baja impedancia que requieran de un manejo intuitivo y tengan un presupuesto ajustado. Incorpora una entrada de línea de 100 V con máxima prioridad y mute por cierre de contactos para integrar en instalaciones con avisos de emergencia. Conectores euroblock, seguros y de fácil conexión. Gran calidad de sonido. Diseño actual y discreto. Tamaño compacto, para uso en sobremesa o anclado en superficie. Estos amplificadores son muy habituales en instalaciones como locales comerciales, centros educativos, museos, salas de exposiciones, bares, restaurantes, etc.



Amplia la información del producto en:

<https://fonestar.com/ES/PROX-15>

CARACTERÍSTICAS TÉCNICAS

CHARACTERISTICS	Public address amplifier USB / MP3 / FM player. Microphone input with mix, gain and priority level control. Tone controls. 100 V and 4 Ω outputs. Mounting in vehicles and desktop.
POWER	15 W RMS
RESPONSE	20-20,000 Hz \pm 3 dB
DISTORTION	Harmonic: <1% at 1 kHz
INPUTS	1 balanced / unbalanced mic, euroblock / 6.3 mm jack, 600 Ω 6 mV RMS 1 auxiliary, euroblock / 2 x RCA, 47,000 Ω 300 mV RMS 1 line 100 V, euroblock
FUNCTIONS	Forced ventilation with variable speed with temperature Light indicators for power on, protection, signal peak and output signal 100 V input priority Mute by contact closure, euroblock
CONTROLS	Microphone volume Selected input volume Input selector USB / MP3 / FM player controls Tone: bass and treble Microphone gain and priority
PLAYER	USB / MP3 player with ambient music playback mode. When turned on, it automatically starts playback in successive order FM digital tuner with presets and automatic search Memory of last selected mode (USB / MP3 or FM), last played song or last tuned station and last selected playback mode
IMPEDANCE	4 Ω and 100 V line, euroblock
POWER SUPPLY	230/115 V AC, 50 W and 12 V DC, 15 W
DIMENSIONS	254 x 84 x 260 mm depth
WEIGHT	3"4 kg
ACCESSORIES	FM antenna
OPTIONAL	PROX-15SP: surface mount bracket



Amplia la información del producto en:

<https://fonestar.com/ES/PROX-15>